



NOTES:
 1) GASKETS BETWEEN FRAME AND ENDBELL/GEARBOX, CONDUIT BOX AND FRAME, AND CONDUIT BOX COVER AND CONDUIT BOX.

CATALOG NUMBER	OUTPUT RPM	FULL LOAD TORQUE LB.-IN.	INPUT HP	OVERHUNG LOAD LBS.	RATIO TO 1
M1125269.00	42	280	1/4	327	58
M1125270.00	83	155	1/4	267	29
M1125271.00	250	45	1/4	201	10
M1125272.00	500	25	1/4	194	5

				TOLERANCES UNLESS SPECIFIED		LEESON	ELECTRIC MOTORS GEARMOTORS AND DRIVES	DRAWN IPG 5/14/05	
				DEC.	INCHES			CHK	SAD
				.X	±.1			APPD	
				.XX	±.03	TITLE	OUTLINE - 32 FRAME DC 90V - PE350 GEARMOTOR	SCALE	1=2
01	1/2 NPT CONDUIT PLUG QTY. WAS 3. ISAAC 08-3457	RPB	7/30/08	BC	.XXX	MAT'L		REF	PRO40127-RD1
00	RELEASED: REF. PRO40127-RD1	IPG	5/14/05	SAD	.XXXX	FINISH		FMF	M1125269.00
NO.	REVISION	BY	DATE	CHK	ANG	±1/2"	PREV		
THIS DRAWING IN DESIGN AND DETAIL IS OUR PROPERTY AND MUST NOT BE USED EXCEPT IN CONNECTION WITH OUR WORK ALL RIGHTS OF DESIGN AND INVENTION ARE RESERVED THIS IS AN ELECTRONICALLY GENERATED DOCUMENT - DO NOT SCALE THIS PRINT				RFP		CAD FILE	M1030991	SIZE	DRAWING NO.
				DIST			B	M1030991.00	REV. 01