

MAXIMUM RATING TABLES

SIZE 860 • GR & EL SERIES



Style B

Style H



Size 860





Ratio	Input RPM	Output RPM	Input HP	Output HP	Output Torque (lb-in)	Left Hand Catalog No.	Right Hand Catalog No.	Double Extension Catalog No.	Hollow Output Catalog No.*
5	2500	500	39.83	38.29	4827	__8600085	__8600090	__8600095	__8600501.XX
	1750	350	35.10	33.70	6068				
	1170	234	29.94	28.69	7726				
	100	20	6.203	5.581	17587				
7.5	2500	333	34.20	32.60	6163	__8600086	__8600091	__8600096	__8600502.XX
	1750	233	29.98	28.52	7704				
	1170	156	25.41	24.11	9740				
	100	13	5.018	4.371	20662				
10	2500	250	28.53	26.90	6782	__8600001	__8600008	__8600015	__8600503.XX
	1750	175	24.99	23.51	8467				
	1170	117	21.17	19.84	10687				
	100	10	4.198	3.542	22324				
15	2500	166	21.95	20.17	7628	__8600002	__8600009	__8600016	__8600504.XX
	1750	116	19.23	17.61	9515				
	1170	78	16.30	14.85	11996				
	100	6.7	3.337	2.623	24797				
20	2500	125	17.93	16.11	8123	__8600003	__8600010	__8600017	__8600505.XX
	1750	87	15.71	14.06	10127				
	1170	58	13.32	11.84	12758				
	100	5.0	2.805	2.078	26194				
25	2500	100	14.89	13.04	8219	__8600087	__8600092	__8600097	__8600506.XX
	1750	70	13.06	11.378	10245				
	1170	46	11.094	9.582	12903				
	100	4.0	2.418	1.678	26436				
30	2500	83	12.73	10.87	8222	__8600004	__8600011	__8600018	__8600507.XX
	1750	58	11.177	9.486	10249				
	1170	39	9.507	7.989	12911				
	100	3.3	2.143	1.400	26480				
40	2500	62	9.922	8.119	8187	__8600005	__8600012	__8600019	__8600508.XX
	1750	43	8.722	7.083	10203				
	1170	29	7.433	5.963	12848				
	100	2.5	1.761	1.042	26260				
50	2500	50	8.226	6.417	8088	__8600006	__8600013	__8600020	__8600509.XX
	1750	35	7.242	5.597	10079				
	1170	23	6.188	4.712	12691				
	100	2.0	1.544	0.823	25925				
60	2500	41	6.977	5.202	7869	__8600007	__8600014	__8600021	__8600510.XX
	1750	29	6.152	4.539	9808				
	1170	19	5.269	3.822	12352				
	100	1.7	1.376	0.669	25283				
80	2500	31	4.130	2.939	5962	__8600088	__8600093	__8600098	__8600511.XX
	1750	21	3.702	2.522	7264				
	1170	14	3.315	2.122	9142				
	100	1.3	0.950	0.382	19249				
100	2500	25	2.849	1.905	4802	__8600089	__8600094	__8600099	__8600512.XX
	1750	17	2.571	1.635	5886				
	1170	11	2.323	1.376	7408				
	100	1.0	0.686	0.244	15389				

How To Build a Part Number For Size GR860, EL860

1. Select partial catalog number from the selection table
2. Replace leading “__” with series code (GR, EL)
3. For hollow output, replace “XX” suffix with bore code (see next page for codes)

Example:

Grove Gear IRONMAN, style B, 5:1 ratio, left hand output
 GR-B860-5-L
 GR8600085

	Style BM			Style HM	Style BMQ			Style HMQ	
									
NEMA C Input Flange ▲	Left Hand Catalog No.	Right Hand Catalog No.	Double Extension Catalog No.	Hollow Output Catalog No.*	Left Hand Catalog No.	Right Hand Catalog No.	Double Extension Catalog No.	Hollow Output Catalog No.*	Ratio
254-6TC	__8600130	__8600135	__8600140	__8600537.XX	__8600289	__8600301	__8600313	__8600597.XX	5
254-6TC	__8600131	__8600136	__8600141	__8600538.XX	__8600290	__8600302	__8600314	__8600598.XX	7.5
213-5TC 254-6TC	__8600043 __8600064	__8600050 __8600071	__8600057 __8600078	__8600527.XX __8600539.XX	__8600255 __8600291	__8600267 __8600303	__8600279 __8600315	__8600587.XX __8600599.XX	10
213-5TC 254-6TC	__8600044 __8600065	__8600051 __8600072	__8600058 __8600079	__8600528.XX __8600540.XX	__8600256 __8600292	__8600268 __8600304	__8600280 __8600316	__8600588.XX __8600600.XX	15
182-4TC 213-5TC	__8600024 __8600045	__8600031 __8600052	__8600038 __8600059	__8600517.XX __8600529.XX	__8600221 __8600257	__8600233 __8600269	__8600245 __8600281	__8600577.XX __8600589.XX	20
182-4TC 213-5TC	__8600102 __8600117	__8600107 __8600122	__8600112 __8600127	__8600518.XX __8600530.XX	__8600222 __8600258	__8600234 __8600270	__8600246 __8600282	__8600578.XX __8600590.XX	25
182-4TC 213-5TC	__8600025 __8600046	__8600032 __8600053	__8600039 __8600060	__8600519.XX __8600531.XX	__8600223 __8600259	__8600235 __8600271	__8600247 __8600283	__8600579.XX __8600591.XX	30
182-4TC 213-5TC	__8600026 __8600047	__8600033 __8600054	__8600040 __8600061	__8600520.XX __8600532.XX	__8600224 __8600260	__8600236 __8600272	__8600248 __8600284	__8600580.XX __8600592.XX	40
182-4TC	__8600027	__8600034	__8600041	__8600521.XX	__8600225	__8600237	__8600249	__8600581.XX	50
143-5TC 182-4TC	__8600028	__8600035	__8600042	__8600522.XX	__8600190 __8600226	__8600202 __8600238	__8600214 __8600250	__8600570.XX __8600582.XX	60
143-5TC 182-4TC	__8600103	__8600108	__8600113	__8600523.XX	__8600191 __8600227	__8600203 __8600239	__8600215 __8600251	__8600571.XX __8600583.XX	80
143-5TC 182-4TC	__8600104	__8600109	__8600114	__8600524.XX	__8600192 __8600228	__8600204 __8600240	__8600216 __8600252	__8600572.XX __8600584.XX	100

▲ Consult Factory for other motor flanges available.

* Catalog numbers are for hollow output shaft reducers.
When ordering, substitute the XX suffix with the required output bore code.

Available bore codes

Fraction Size	2"	2-3/16"	2-1/4"	2-7/16"	2-1/2"	2-11/16"	2-5/16"	3"	3-3/16"	3-7/16"
Decimal Size	2.000	2.188	2.250	2.438	2.500	2.688	2.938	3.000	3.188	3.438
Output Bore Code	32	35	36	39	40	43	47	48	51	55

QUICK REFERENCE

DIMENSIONS

GR SERIES Pages 52-73 **ACCESSORIES** Pages 284-295
EL SERIES Pages 94-109 **OVERHUNG LOADS**..... Pages 660-662